GOOD TAKE

Photo Module for PCM Remote Control Systems

Description

The AT138B is miniaturized receiver for use infrared carrier frequency PCM remote control systems. A photo PIN diode and a low noise preamplifier are assembled on lead frame, the epoxy package is designed as IR filter.

The demodulated output signal can directly be decoded by a microprocessor. The main benefit is the reliable function even in disturbed ambient and the protection against uncontrolled output pulses.



Features

- Photo detector and Preamplifier in one package
- Internal filter for PCM frequency
- TTL and CMOS compatibility
- Output active low
- Low current dissipation
- Suitable burst length ≥ 10 cycles/burst

• Lead-Free component in accordance with RoHS directives

Applications

TV, VTR, Acoustic Devices, Air Conditioner, Car Stereo Units, Computers, Interior controlling appliances, and all appliances that require remote controlling

Special Features

disturbance light

the output

• Enhanced immunity against all kinds of

• No occurrence of disturbance pulses at

Block Diagram



CONTAKE

OODTAKE

GOOD TAKE

Application Circuit



*) recommended to suppress power supply disturbance

Absolute Maximum Ratings



Tamb = 25 °C	TAKL			
Parameter	Test Conditions	Symbol	Value	Unit
Supply Voltage	(Pin 3)	Vs	6.0	V
Supply Current	(Pin 3)	Is	5	mA
Output Voltage	(Pin 1)	Vo	6.0	V
Storage Temperature Range		Tstg	-30+105	°C
Operating Temperature Range		Tamb	-25+85	°C
Power Consumption	$(Tamb \leq 85 \ ^{\circ}C)$	ptot	50	mW
Soldering Temperature	$t \leq 5s$, 1 mm from case	Tsd	260	Ċ
		•	60	

Basic Characteristics

Tamb = 25 $^{\circ}$ C

Parameter	Test Conditions	Symbol	Min	Тур	Max	Unit
Supply Current (Pin3)	Vs = 5V, Ev = 0	Isd	0.7	1.1	1.4	mA
Supply Voltage (Pin3)	0011	Vs	4.5		5.5	V
Transmission Distance	IR diode AT205, $IF = 400 \text{ mA}$	d	20			m
Output Voltage High (Pin1)	Vs = 5V	Vosh	4.5			V
Output Voltage Low (Pin1)	Cycle 1.2mS, 50% duty	Vosl			250	mV
Level Output Pulse Width	Burst Wave= 600µs,	Тwн	400		800	μs
Level Output Pulse Width	Cycle 1.2mS, 50% duty	Twl	400		800	μs
Carrier frequency		fo		37.9		kHz
Peak Wavelength		λ		940		nm
Directivity	Angle of half transmission distance	φ1/2		±45		deg
					COL	

CONTAKE

GOOD TAKE

Package Outline

Dimensions in mm: tolerance ±0.3mm







GOODTAKE

GOODTAKE



CONTAKE